

A. Descriptive Title Of The Invention:

A System For Remotely Adjusting Antennas

B. Cross Reference To Related Applications:

None

C. Statement Regarding Federally Sponsored R & D:

None

D. Reference To A "Microfiche Appendix":

None

E. Background Of The Invention

Field Of The Invention-

This invention describes a method, an apparatus, and a system for remotely adjusting by mechanical and electronic means the plumb-to-level and the compass heading of one or a plurality of communication antennas. The term plumb-to-level will be used throughout this description to represent absolute measurements with respect to true vertical. And, the term compass heading will be used throughout this description to represent absolute compass heading direction with respect to magnetic North.

A continuing problem for cellular telephone network planners is that of base station over or under coverage. That is, if the overlapping area between two cells is too large (i.e., over coverage), increased switching between the base station (handoff) occurs, which strains the system.

Likewise, if the overlapping area between two cells is too small (i.e., under coverage), gaps in service, or nodes, will occur. There may even be interference with other cellular networks using the same, or nearby, operating frequencies. To minimize the over and under coverage effects, a cost effective means to precisely position the antenna remains a continuing challenge.

This invention is not limited to antennas for cellular telephone network use only, but since this is the largest use, we will use this application in the following description. In general, radio frequency antennas are described as having a radiation pattern that is referred to as being a horizontal pattern and a vertical pattern, with the former being referenced along the horizon, as would a compass heading, and the latter being referenced from the vertical, as would plumb-to-level. Since cellular telephone traffic tends to concentrate in certain areas such as along a busy

highway, further performance optimization is accomplished by the ability to precisely position the antenna in a concentrated area.

The industry term for antenna position with respect to vertical angle is down-tilt. The term for antenna position with respect to horizontal angle is azimuth. Measurements of plumb-to-level (P-L) and compass heading (CH) are absolute and are referenced to the earth itself. Current methods for obtaining antenna settings such as down-tilt angle are measured with respect to a part of the tower itself. In the case of most radio antennas, this measurement is made with respect to the tower. However, these tower referenced measurements are subject to many induced errors caused by weather, ground shifting, disturbances, or human error that is inherent to the measurement process itself. Once the reference is flawed, then all the calibrations based upon the reference are in error.

There are several ways to adjust antenna down-tilt. One way is to adjust it electronically by using a phased-array antenna. Another way is by mechanical means, as in using a special down-tilt mounting bracket such as the EZ-Tiltz™ bracket. The mechanical method is the simplest method since it does not require sophisticated timing and electronic phasing circuits. A third way to adjust the antenna down-tilt is to use closed loop electro-mechanical control devices using encoders. Because of the reference issue described above, this method is also flawed, and care must be taken to use components that are compatible with electro-magnetic interference (EMI) sensitive communication electronics. The use of high frequency devices such as stepping motor drives is not recommended.

Unfortunately, antenna optimization that is accomplished by solely adjusting the down-tilt alone is limited. Improvements made by adjusting the down-tilt are only valid for one direction of the horizontal radiation pattern. Within the most critical range of down-tilt, the actual radiation coverage varies more according to the azimuth direction, but demonstrates that both the down-tilt and the azimuth adjustments are integral. A change results in a horizontal radiation half-power beam width which gets broader with increasing down-tilt angle rather than the desired narrower, more focused radiation beam. Since azimuth adjustments for antenna sectors (more than one antenna acting as one antenna) are difficult to adjust manually and are not available electronically, site planning personnel to date have not been able to accurately compensate for this effect. Site surveys provide P-L and CH information. Until now, only fixed, manual adjustments referenced to points on the tower are assumed to be accurate. This invention allows remote adjustments with absolute reference to survey data.

Cellular telephone network antenna systems found in the center of a "cell" usually consist of three sectors, positioned at 120° segments of the complete circle. Each sector usually consists of four antennas mounted on a common mounting bar. From this, it can be seen that a typical cellular telephone antenna site can have up to twelve antennas needing periodic adjustment. This is very labor intensive and expensive, and usually involves dangerous work high above the ground.

Description Of Related Art-

Singer et al., US Patent Number 6,239,744 B1, teaches a method for adjusting antenna down-tilt, but only from a broad-brush perspective. Singer fails to address the need for azimuth adjustments in order to optimize beam coverage of a specific location when consideration is given to traffic patterns, topography, and other networks. Further, the Singer patent is based on the use of built-in controllers for each antenna and antenna sector, remembering stored data, and utilizing local and remote displays. In Singer, sensing down-tilt position of the antenna is left to an angle decoder to determine the angle between the antenna and its mounting structure, but does not address the need to coincide site survey data and actual site conditions. Much attention is given to operational function in Singer, but little attention is given to indicate how the actual hardware, or any integrated system, may be created by following its teachings.

Zimmerman et al., US Patent Number 6,232,928, Bernier, US Patent Number 5,029,179, and Chavez, US Patent Number 5,963,179, all teach manually adjusted down-tilt or azimuth antenna brackets. No mention of a remote means of adjustment is made.

Fulop, US Patent Number 5,583,514, teaches a satellite antenna position optimization system that is fast, complicated and expensive, suitable for government satellite tracking, but not suitable for low cost commercial installations such as that required by small cellular antenna sites. Fulop teaches a method of using GPS data to establish antenna position, which is outside the scope of this invention.

Hill, US Patent Number 5,461,935, teaches a slip clutch linear actuator. This design is fatally flawed because over travel of the actuator could cause the mechanism to bind. With the spring loaded clutch, actuators are limited to a fixed amount of torque. If this torque limit is exceeded, the drive reaches a point of slippage, thereby causing an irreversible jamming condition due to limited torque settings of the slip clutch.

F. Summary Of The Invention

Objective And Advantages-

This invention addresses the disadvantages of current equipment and techniques, and provides the industry with an economical and efficient method of making remote P-L and CH adjustments of multi-antenna sectors typically found at cellular telephone networks.

5 In a typical cellular telephone network, base station performance deteriorates quickly due to over coverage and under coverage. It is the objective of this invention to provide a method and a hardware/software system to effectively optimize cellular network antennas by remotely adjusting antenna P-L and CH to eliminate over coverage and under coverage.

10 Antenna adjustments that are referenced to the support structure such as Singer are subject to many errors caused by weather, ground shifting, or disturbances due to the measurement process itself. Once the reference is flawed, then all the measurements based on that reference become corrupted. It is the objective of this invention to provide measurements and adjustments of down-tilt and azimuth that are made with respect to absolute geodetic measurements of P-L and CH.

15 Antenna site survey data is based on absolute P-L and CH information. To date, only fixed, manual adjustments of antenna down-tilt and azimuth can be made. It is the objective of this invention to provide a method for remote adjustments and measurements based on the same frame of reference.

20 Current methods of down-tilt adjustment of antennas by elaborate electronic means are limited and expensive. It is the objective of this invention to provide an electro-mechanical method of not only P-L adjustment, but also of CH adjustment by a simple, cost effective means that does not require sophisticated timing and electronic phasing circuits.

25 Due to the sensitive nature of communications circuits, extreme care must be taken to use components that are compatible with their electro-magnetic interference (EMI) sensitive circuits. The use of devices that emit high frequency interference such as stepping motor drives is not recommended. It is the objective of this invention to construct a remote antenna P-L and CH adjustment system using reliable, EMI free, motors and drives. Additionally, the invention of this application teaches a technique for preventing actuator damage by utilizing reversing relay limit switches.

35 Since convenient azimuth adjustments for antenna sectors (an array of more than one antenna acting as one antenna) are difficult to adjust manually, and until now are not available

electronically, site planning personnel have not been able to take this problem into consideration. It is the objective of this invention to provide a simple, low cost and remote method for making CH adjustments without having personnel climb to the top of towers or other similar structures.

Since up to twelve antennas may make up a typical cellular antenna site, with all needing periodic adjustment, manually making down-tilt and azimuth adjustments is very labor intensive and expensive, and usually involves dangerous work high above the ground. It is the objective of this invention to improve and simplify the process of remotely and quickly adjusting antenna P-L and CH, with economical, cost effective hardware, and without the need for personnel to climb any towers or similar structures.

Systems that provide on site power and control of antenna adjustments may experience occasional tampering or interference by stray electrical transients. It is the objective of this invention to provide a secure, cost effective solution to the antenna adjustment requirement by providing a system that does not require on site power and computing or controlling capability. Additionally, one set of equipment may be used on many antenna sites by a single technician.

The details and many of the advantages provided by this invention will become clear and will be better understood by reviewing the following description and accompanying drawings, wherein: the preferred embodiment offers a system for remotely adjusting the P-L and CH of one or a plurality of communication antennas.

G. Description Of The Drawings

Figure 1 is a typical antenna sector mounted atop a tower showing major components of the invention

Figure 2 is an upper bracket.

Figure 2a is a lower bracket.

Figure 3 is an antenna sector with P-L and CH actuators

Figure 4 is an antenna sector with P-L and CH positioners

Figure 4a is an antenna sector with P-L and CH, (cut away showing P-L at its maximum)

Figure 5 is a linear actuator,

Figure 5a is a linear actuator (full half sectional view showing internal part detail)

Figure 5b is a linear actuator (cut away full sectional view showing more detail in the motor-drive screw area)

Figure 6 is a system block diagram

Figure 6a is a system block diagram, showing details of the interface module

Figure 7 is a software block diagram

H. Detailed Description

Fig. 1, shows a communications antenna system having, typically, four duplex transmitting and receiving cellular antennas mounted as a sector atop a suitable structure such as, for example, a tower. Furthermore, each cellular system tower may have up to three such sectors, each sector covering a segment that is usually 1/3 of a circle (120°). Referring to Fig. 1, a system for remotely adjusting the P-L and CH of one or a plurality of communication antennas, the subject of this invention is shown comprising: an antenna sector optimizer 10, mounted atop a tower, one or more weatherproof field interconnection boxes 60 and 64, an interconnection cable 62 running between the field boxes, one or more DC power sources 68 and 70, and a laptop computer 66. Although four antennas are shown to represent a sector in Fig. 1, this is not intended to be a limitation in scope, as one or a plurality of antennas may comprise a sector as defined by this invention. It is within the scope of contemplation of the inventor that the tower might be a building, a wall, or other appropriate manmade or natural structure. Furthermore, there may be one or a plurality of field boxes used, even though Fig. 1 shows two boxes being used. The invention will work equally as well with one or many field boxes being used. Also, Fig. 1 identifies a wire cable as the interconnection cable 62, however, future technology might allow this cable to be fiber optic or other interconnection means. Although Fig. 1 shows two DC power sources, it is within the scope of contemplation that any suitable power source such as, but not limited to, AC line power, "green" power, generator power, or similar power sources, could power this system. And finally, even though Fig. 1 depicts a laptop computer, it is highly likely that a remote mainframe or desktop computer may also be utilized to practice this invention.

Fig. 2 depicts the upper down-tilt bracket 18. Fig. 2a depicts the lower down-tilt bracket 20.

Fig. 3 is a cutaway view of the antenna sector optimizer 10, showing two antennas making up the sector. Although Fig. 3 shows only two antennas making up the sector, it is within the scope of contemplation that any number of antennas may be used to make up the sector. The antennas 12 are firmly attached to the tower by way of a mounting bar 40, normally one of three positioned to form a triangle at the top of the antenna tower. These bars are welded to the tower thereby providing a fixed, rigid attachment. Each antenna 12 of the sector is attached to an individual electromechanical linear actuator hereinafter referred to as the P-L actuator 14. The preferred embodiment of this invention utilizes the EZ Actuator™ linear actuator, however, other suitable linear actuators may be used to practice this invention. The antenna 12 of the sector is attached to the P-L actuator 14 by an upper down-tilt bracket 18 and a lower down-tilt bracket 20 (Fig. 2

and Fig. 2a). Although the preferred embodiment of this invention utilizes the EZ Tiltz™ brackets, any other suitably configured tilt brackets may be used to practice this invention. Another key bracket is the actuator bracket 28. The P-L actuator 14 is attached to the mounting bar 40 by an actuator bracket 28 and to the antenna 12 using the upper down-tilt bracket 18 and the lower down-tilt bracket 20. The assembly of these components provides the tilt adjustment of the antenna sector optimizer 10.

Referring again to Fig. 3, in order to provide CH adjustment to the antenna 12, the antenna sector optimizer 10 is provided with an additional electromechanical linear actuator hereinafter referred to as the CH actuator 16. The preferred embodiment of this invention utilizes the EZ Actuator™ linear actuator, however, other suitable actuators, linear or otherwise, may be used to practice this invention. The CH actuator 16 is attached to the mounting bar 40 using a pair of U-bolt or universal fasteners 26 (only one is shown in the cutaway view). Each individual P-L actuator 14 is attached to a CH tie bar 30 through a pair of pitman arms 24. The CH tie bar 30 is attached to the top of the CH actuator 16 with an additional upper down-tilt bracket 18. The assembly of these components provides the CH adjustment of the antenna sector optimizer 10.

Fig. 4 depicts an end view of the antenna sector optimizer 10 with the P-L actuator 14 in its minimum position and the antenna 12 in its least tilted position. A cutaway view, Fig. 4a, shows the same detail, but with the P-L actuator 14 in its extended position, and the antenna 12 in its full tilt position. Fig. 4 shows that the lower down-tilt bracket 20 has one hinged part, and is clamped to the lower half of the P-L actuator 14 at a fixed position. Further, Fig. 4 shows the lower down-tilt bracket 20 is bolted to the bottom area of the antenna 12. It shows that the upper down-tilt bracket 18 is hinged in two places, and is attached at the top of the P-L actuator 14 and to the top area of the antenna 12. This double hinge action makes the top of the antenna 12 tilt forward as the P-L actuator 14 is extending, and conversely, it makes the top of the antenna 12 tilt backward when it is contracting.

Continuing to refer to Fig. 4, the actuator bracket 28 is a casting or weldment forming a vertical surface having a tangentially positioned vertical tube on its back side. The P-L actuator 14 is inserted into the tube. Heavy grease is packed between the actuator and the inside of the tube as a means of dampening the rotational motion of the P-L actuator 14 caused by wind loading and other vibrational forces exerted on the antenna. The P-L actuator 14 is held vertically in place by a pair of pitman arms 24, one located above the tube and one located below the tube. The pitman arms 24 limit the up and down movement of the P-L actuator 14, and allow it to rotate with respect to the actuator bracket 28. The pitman arms 24 are in turn attached to a CH tie bar

30 using pitman arm attachment pins 32. Movement of the CH tie bar 30 causes all pitman arms to move such that the P-L actuators 14 attached to each and every antenna 12 in the sector rotate (change CH) together, thereby causing a uniform redirection of the antenna sector CH.

5 The CH tie bar 30 is attached to the CH actuator 16 by the upper tilt bracket 18. This bracket has two hinges and is the same as the upper tilt bracket 18 used to attach the antenna 12 to the P-L actuator 14. As the CH actuator 16 extends from its minimum length to its maximum length, the P-L actuators 14, and thereby, the antennas 12 rotate through their full sweep of CH rotation.

10 Also shown in Fig. 4, are the CH detector 52 and the P-L detector 50.

Antenna Sector P-L/CH Actuator

15 Fig. 5 shows a side view of an actuator 100 used in this invention for both the P-L actuator 14 and the CH actuator 16. Both of these actuators (14 and 16) are motor driven linear actuators. In this invention, the EZ Actuator™ linear actuator is used for the P-L actuator 14 and the CH actuator 16. It is within the scope of contemplation of this invention that other suitable linear actuators may be used.

20 The actuator 100 comprises three main parts, the actuator crown 102, the dust shield 108, and the main body extrusion 122. During normal operation, power being applied to the internal motor, (as described below) causes the linear actuator to increase or decrease its length, and the distance between the actuator crown 102 and the main body extrusion 122 changes accordingly.

25 Details of the actuator 100 may be seen by referring to Fig. 5a. For greater detail, refer to the cutaway view of the central section of the actuator, Fig. 5b. The actuator crown 102 seats inside the top of the dust shield 108 and is pinned in place. The dust seal bearing 114 snaps in place in the bottom of the dust shield 108 with 3 interlocking rings set into matching grooves on the inside of the dust shield 108. The linear ram 116 fits into a square socket on the bottom of the actuator crown 102 and is held in place by the same pins that hold the actuator crown 102 to the dust shield 108. The dust seal bearing 114 slip fits over the outer diameter of the main body extrusion allowing movement up and down without allowing exterior particle contaminants to enter past the seal. The spines 120 fit into a channel inside the main body extrusion 122. The motor mount 126 holds the motor 180 and the electronics control board (not shown) in the bottom of the main body extrusion 122. Appropriate slots in the surface of the motor mount 126 allow the placement of the spines 120 between the exterior of the motor mount 126 and the interior of the main body extrusion 122. The drive coupler 176 is attached by threads and a counter screw to the drive end

of the motor **180**. The drive coupler **176** slip fits into the bottom of the drive shaft **170** and is held in place by the roll pin **174**. The anti-rotate lock cap **178** press fits around the bottom end of the drive shaft **170** and is secured in place by the same roll pin **174** that allows the drive coupler **176** to turn the drive shaft **170**. The spring loaded drive socket **164** is press fit into the top end of the drive shaft **170**. The geometry of the drive coupler **176** creates a linear movement in the drive shaft **170** and communicates with the anti-rotate lock cap **178** just before rotation begins. Lock teeth geometry at the interface of the anti-rotate lock cap **178** and the motor mount **126** prevent rotation of the mechanism when the motor **180** is not active and turning in either direction. This action defines the actuator's mechanical braking function. Four bolts hold the bottom of the spines **120** and the motor mount **126** to the main body extrusion **122**.

The drive shaft bearing spacer **172** is seated in the spines **120** and centers the drive shaft **170**. The drive nut **162** is screwed halfway onto the bottom end of the all-thread **118**. The lock bolt **165** is screwed into the bottom portion of the drive nut **162** against the face of the all-thread **118**, this locks the drive nut **162** and all-thread **118** together. The bearing block with thrust bearings **158** is located on the all-thread **118** between the drive nut **162** and the bearing position lock nuts **156**. The linear ram nut **152** is positioned an appropriate distance away from the top of the bearing position lock nuts **156** on the all-thread **118**. The linear ram nut **152** is pinned to the inside bottom of the linear ram **116**. The two ram bearing guides **110** are appropriately positioned to prevent the linear ram **116** from flexing out of alignment or rotating in its housing during operation. The all-thread end lock nuts **106** are screwed onto the top end of the all-thread **118**.

The limit switch rod position lock nuts **154** are placed on the limit switch rod **150** at the top and at the bottom so that when the linear ram nut **152** moves and contacts one of the limit switch rod position lock nuts **154**, it moves the limit switch rod **150** up or down accordingly. The limit switch rod **150** then moves the limit switch trigger block **168** up or down accordingly. The limit switch trigger block **168** then activates the limit switch **166** sending a signal to the field box(es) that the actuator (P-L actuator **14** or CH actuator **16**) are at the end of their designed travel limit. A reversing relay immediately switches polarity to the drive motor. That relay is actuated by the limit switch. A capacitor is then positioned across the reversing relay coil. This capacitor provides a specific amount of time for the motor to reverse thus giving the trigger block sufficient time to clear the limit switch and eliminate bounce-back. Simultaneously, when the reversing switch is actuated, it closes a set of contacts that alerts the computer that the end of travel has been reached.

In an alternative embodiment of this invention to allow a cost effective solution to the problem of sweeping one or a plurality of antennas from one sector to another sector of the same cell site array, and then compliment the new P-L and CH settings of their new sector. This cost effective solution allows the system to balance sector traffic loads and access underutilized capacity in sectors that have capacity to spare.

Field Connection Interface

Fig. 6 is a signal block diagram for the system for remotely adjusting the P-L and CH of one or a plurality of communication antennas showing the antenna sector optimizer, the field box(es), the laptop computer, and the DC power sources.

Referring to Fig. 6, the P-L portion comprises a P-L actuator 14 and a P-L detector 50. The CH portion comprises a CH actuator 16 and a CH detector 52. Both actuators, in the preferred embodiment, are powered by standard DC motors. When DC power is applied with a positive polarity to the actuator, the actuator increases in length. When DC power is applied with a negative polarity to the actuator, the actuator decreases in length. When the motors are not being actuated, a shorting resistor is placed across the terminals of the motor thereby creating a method for dynamic braking.

There is one P-L detector 50 and one P-L actuator 14 for each antenna in the sector. A sector typically has from one to four antennas. The P-L detector 50 detects the antenna P-L with respect to true vertical or horizontal. Unlike sensors that measure antenna angle with respect to a tower member, this novel invention automatically eliminates errors caused by unavoidable changes in the base reference by using a P-L detector that incorporates an encapsulated electrolyte solution. In the preferred embodiment, this is a dual axis DX-045 detector sold by AOSI of Linden, NJ.

Each antenna sector has a CH actuator 16 to adjust the CH or direction of the entire antenna sector. Each sector also has a CH detector 52 for determining the actual CH of the sector. There is one CH actuator 16 and one CH detector 52 for each sector. A tower or site, may have multiple sectors. In the preferred embodiment, the CH detector used is a model TCM2-20 sold by PNI Corporation of Santa Rosa, CA.

So that each antenna and each sector may be adjusted independently, each actuator (both P-L actuators and CH actuators) has a separate activation relay for the detector and separate activation relay for the actuator motor. This allows all antennas to be independently monitored

and adjusted using one set of field boxes and one laptop computer by simply addressing each antenna P-L or each sector CH. An activation relay for the P-L actuator 14 is housed in the P-L actuator 14. An activation relay for the CH actuator 16 is housed in the CH actuator 16. An activation relay for the P-L detector 50 is housed inside the P-L actuator 14. An activation relay for the CH detector 52 is housed inside the upper field box 60. In the preferred embodiment, wires from the P-L detectors 50 are connected to their respective actuators. Wires from the CH detectors 52 are connected to the upper field box 60. Wires from all actuators are connected to the upper field box 60.

The field box 60 contains electronic circuitry to provide the signal conditioning and the logic selection for the specific antenna and/or sector being addressed. The P-L detector 50 is connected to the electronic P-L circuit board 74 wherein the amount of deviation from true P-L (that is, with respect to the earth's gravity) is converted into a 0-5VDC signal. This signal, in turn, is converted to an 8 bit digital signal by the analog to digital converter 76 that is compatible with the laptop computer 66.

The CH detector 52 is connected to the electronic compass circuit board 84 wherein the amount of deviation from true North (that is, with respect to the earth's magnetic field) is converted into a 0-5VDC signal. This signal, in turn, is converted to an 8 bit digital signal by the analog to digital converter 86, which is compatible with the laptop computer 66.

In Fig. 6a, the interface module 90 relays the logical addressing and data reading function in response to commands given by the laptop computer 66. Eight bit binary data from each detector is converted into two, 4 bit binary bytes by each of two octal bus line drivers 92 and 94. The byte is selected by the laptop computer. Further, a third octal bus line driver 96 selects which of the two data sources the laptop computer is reading at any one time. Here, the laptop computer selects which detector is being read. This conversion allows the data from the two detectors to be transferred to the laptop computer over four wires, rather than the sixteen wires that would normally be required. Also, by addressing each antenna and each sector separately, the number of sets of wires needed to read all the data is substantially reduced from a maximum of 19 sets to just the 1 set. The 4 to 16 Line Decoder/Demultiplexer 98 selects the detector relay and the actuator relay that is requested by the laptop computer. This is not meant to be a limitation, but rather it is within the scope of contemplation of this invention that the 4 to 16 Line Decoder/Demultiplexer 98 could be potentially expanded to include additional such devices.

Referring again to Fig. 6, to insulate the electronic circuits in the field boxes to transients and other electrical disturbances that may cause damage or malfunction, each box is provided with optical isolation circuits for each communication line. In the preferred embodiment, there are two boxes requiring two optoisolators 91 and 93.

In the preferred embodiment, there are two identical sources of power, 68 and 70, both of which are standard rechargeable 18 VDC battery packs. DC power 1 68 is connected to a voltage regulator circuit 72 thereby creating regulated voltages Vcc and 9_Vdc. These regulated voltages are needed to power the logic contained in the field boxes 60 and 64, and the electronic compass 84 as part of the antenna sector optimizer 10, and the electronic P-L board 74.

In response to a command from the laptop computer, a forward/reversing relay 88 reverses the polarity of the 18VDC power circuit used to drive the P-L actuator 14 and the CH actuator 16 when it is desired to increase or decrease the length of either actuator.

In the preferred embodiment, power, control and computing functions are brought to and applied to the system by the technician while making adjustments. This is to prevent tampering or sporadic responses to outside disturbances, as would be possible in a system with on site power and control capability. Also, another benefit of portable power and user furnished computing equipment, allows the same equipment to be used on many antenna sites, thereby providing an additional cost effective solution to the optimization process.

Laptop Computer and Application Software

The key to the performance of this system for remotely adjusting the P-L and CH of one or a plurality of communication antennas is in the antenna optimization application software. In the preferred embodiment, the antenna optimization application software is run on a laptop computer. The computer having the antenna optimization application software allows the operator to remotely adjust the P-L of any antenna or the CH of any antenna sector merely by connecting the laptop computer to the optimizer system at the lower field box. This eliminates the need for the technician to climb the antenna tower. By connecting the DC power source along with the laptop computer, the technician may perform the necessary optimization adjustments without the need for any other additional outside resources.

The system for remotely adjusting the P-L and CH of one or a plurality of communication antennas is not limited to use by a locally connected laptop computer. An alternative embodiment might utilize an on site desktop computer. Another alternative embodiment might

utilize a mainframe computer. It is contemplated that computers located at other sites, connected by wire or modem, may also be used.

The antenna optimization application software can run on almost any personal computer (PC) with minimal specifications. The PC may be any one of the standard microprocessor types commonly found in use. Since large amounts of processing power is not necessary, any suitable 8 bit or greater microprocessor, such as for example an Intel 86286 or greater, with a processing speed of 20 MHz. or greater, may be used. The PC should have at least one standard parallel port, and a standard display. It need not have sound reproduction capability.

The application software for remotely adjusting the P-L and CH of one or a plurality of communication antennas operates under any version of MS Windows or other standard operating system that employs a similar architecture.

A block diagram of the application software is provided in Fig. 7a through Fig. 7o. The application software 200 comprises an initialization routine 202, followed by two operator prompts, connect to parallel port 204 and connect power source 206, and a routine calibrating the electronic P-L and CH 208. If wind is present 210, the program branches to prolonged sampling 211. If not, the program maintains its normal sampling and advances directly to the additional prompts. The program prompts the user to input the number of antennas in the array 212 (n), and input the number of antennas per sector 214 (n'). Then the program reads the P-L value from each antenna and the CH value from each sector, and stores the values in a memory array 216.

The user is asked to select one of eight options 218. If option 1 (Display All Current Antenna P-L) was selected 220, the program branches to the option 1 routine. Option 1 proceeds to set the antenna address to 1 224, read a new P-L value from the selected antenna 226, store it in the memory array and increment the antenna number 228, and pause 0.5 seconds to stabilize the system 230. If the antenna number is $n+1$ 232, all the P-L values from the array are displayed 234, followed by a return to the selection screen 236. If the antenna number is not $n+1$ 232, then the program returns to read a new P-L value 226.

If the one of eight options 218 chosen was not option 1, then the program will test to see if option 2 was selected 238. If option 2 (Adjust Individual Antenna P-L) was selected, then the program branches to the option 2 routine. Option 2 proceeds to initiate the antenna adjustment routine where the user is prompted for the antenna address to be adjusted 242, actuates the address of the selected antenna 244, read a new P-L value 246, displays the new P-L value, prompts the

user for a desired P-L value **248**, and determines if the new P-L value is smaller than the desired P-L value **250**. If the new P-L value is smaller, the program branches to actuate the P-L actuator motor in a reverse direction **252** before proceeding to the next operation. Or, if the new P-L value is not smaller, the program continues to actuate the P-L actuator motor in a forward direction **254**.

5 The program reads a new P-L value **256** and checks to see if the new P-L value is within 0.1 degree of the desired P-L value **258**. If the answer is no, the program returns to get another new P-L value **256**. If the answer is yes, the program stops the P-L actuator motor **260**, pauses 1 second **262**, and gets a new P-L value **264**. If the new P-L value is not within 0.1 degree of the desired P-L value, the program returns to check if the new P-L value is smaller than the desired
10 P-L value **250**. If the new P-L value is within 0.1 degree of the desired P-L value, the program continues and displays the new P-L value **270** and returns to the selection screen **271**.

If the one of eight options **218** chosen was neither option 1 nor option 2, then the program will test to see if option 3 was selected **272**. If option 3 (Adjust Complete Sector P-L) was selected, then the program branches to the option 3 routine. Option 3 proceeds to prompt the user for the sector number **276**, prompt the user for a desired P-L value **278**, selects the address of the first antenna in the sector and gets the new P-L value **280**. The program tests to see if the new P-L value is smaller than the desired P-L value **282**. If the new P-L value is smaller than the desired P-L value, the program branches to actuate the P-L actuator motor in a reverse direction **284**
15 before proceeding to the next operation. Or, if the new P-L value is not smaller than the desired P-L value, the program continues to actuate the P-L actuator motor in a forward direction **286**. The program reads a new P-L value **288** and checks to see if the new P-L value is within 0.1 degree of the desired P-L value **290**. If the answer is no, the program returns to get another new P-L value **288**. If the answer is yes, the program stops the P-L actuator motor **292**, pauses 1
20 second **294**, and reads a new P-L value **296**. If the new P-L value is not within 0.1 degree of the desired P-L value, the program returns to check if the new P-L value is smaller than the desired P-L value **282**. If the new P-L value is within 0.1 degree **298**, the program increments the antenna address **300** and pauses for one second **302**. If the antenna number is not $n'+1$ **304**, the program returns to check if the new P-L value is smaller than the desired P-L value **282**. If the
25 antenna number is $n'+1$, the program continues and displays the new P-L value **306** and returns to the selection screen **308**.

If the one of eight options **218** chosen was not any of the options 1 through 3, then the program will test to see if option 4 was selected **310**. If option 4 (Adjust Complete Array P-L) was
35 selected, then the program branches to the option 4 routine. Option 4 proceeds to prompt the user for a desired P-L value **314**, set the antenna address to 1 **315**, activate the antenna address

for the first antenna 316, and get a new P-L value 318. The program tests to see if the new P-L value is smaller than the desired P-L value 320. If the new P-L value is smaller than the desired P-L value, the program branches to actuate the P-L actuator motor in a reverse direction 324 before proceeding to the next operation. Or, if the new P-L value is not smaller than the desired P-L value, the program continues to actuate the P-L actuator motor in a forward direction 322. The program reads a new P-L value 326 and checks to see if the new P-L value is within 0.1 degree of the desired P-L value 328. If the answer is no, the program returns to get another new P-L value 326. If the answer is yes, the program stops the P-L actuator motor 330, pauses 1 second 332, and reads a new P-L value 334. The program then checks to see if the new P-L value is within 0.1 degree of the desired P-L value 336. If the new P-L value is not within 0.1 degree of the desired P-L value, the program returns to read a new P-L value 318. If the new P-L value is within 0.1 degree of the desired P-L value, the program increments the antenna address 338 and checks to see if the antenna number is $n+1$ 340. If the antenna number is not $n+1$, the program returns to activate the antenna address 316. If the antenna number is $n+1$, the program returns to the selection screen 342.

If the one of eight options 218 chosen was not any of the options 1 through 4, then the program will test to see if option 5 was selected 344. If option 5 (Exit Program) was selected, then the program branches to the option 5 routine. Option 5 proceeds to display the exit statement 346 and stop the program 348.

If the one of eight options 218 chosen was not any of the options 1 through 5, then the program will test to see if option 6 was selected 350. If option 6 (reserved for future program- Initiate Auto EZ Optimizer) was selected, then the program branches to the option 6 routine. Option 6 is reserved for a future routine 352 whereby the antennas can be monitored and adjusted by way of the internet, intranet, or other modem based communication means.

If the one of eight options 218 chosen was not any of the options 1 through 6, then the program will test to see if option 7 was selected 354. If option 7 (reserved for future program- Adjust Electronic Tilt) was selected, then the program branches to the option 7 routine. Option 7 is reserved for a future routine 356 that will allow the operator to adjust an antenna that has an internal electronic tilt system.

If the one of eight options 218 chosen was not any of the options 1 through 7, then the program will test to see if option 8 was selected 358. If option 8 (Adjust Sector CH) was selected, then the program branches to the option 8 routine. Option 8 proceeds to prompt the user to select the

sector 364, actuate the address of the selected sector 366, read a new CH from the electronic compass, and display the CH 368. The routine then prompts the user for a desired CH 370, and tests to see if the new CH is smaller than the desired CH 372. If the new CH is smaller than the desired CH, the program branches to actuate the CH actuator motor in a reverse direction 376 before proceeding to the next operation. Or, if the new CH is not smaller than the desired CH, the program continues to actuate the CH actuator motor in a forward direction 374. The program reads a new CH 378 and checks to see if the new CH is within 0.1 degree of the desired CH 380. If the answer is no, the program returns to get another new CH 378. If the answer is yes, the routine stops 382. If option 8 was not selected 358, the program proceeds to try again by prompting the user for a new option 362.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2